

POWER DIVIDERS AND COMBINERS

Freq. Range (GHz)	Model No.	Max. Inser. Loss* (dB)	Min. Isol. (dB)	VSWR Max. In/Out	Max. Balance		Average Power † Load VSWR (Watts)			Fig.	Price 4-9 PCS
					(dB)	(Deg.)	1.20	2.0	∞		
8 WAY											
0-3.0	PD108-□/□	15.0	45	1.20/1.20	0.20	2.0	3.0	0.8	0.2	34	\$ 325.00
0-3.0	PD908-□/□	24	35	1.30/1.30	0.20	2.0	0.1	0.1	0.1	38	\$ 245.00
0.01-0.60	PDK-A17-□/□	2.0	35	1.35/1.35	0.30	3.0	1	1	0.1	38	\$ 210.00
0.40-2.0	PDR-200B-8M	0.6	19	1.40/1.35	0.30	4.0	30	20	3	11F	\$ 525.00
0.5-1.0	PD-0510-8M	1.00	20	1.30/1.30	0.40	4.0	2	-	-	80	\$ 305.00
0.5-1.0	PD-1005-8M	0.70	20	1.30/1.30	0.25	3.0	1	-	-	11A	\$ 497.70
0.5-2.0	PDR-200A-8M	0.80	18	1.50/1.35	0.35	5.0	30	10	1	3	\$ 250.00
0.5-2.0	PDRM-6806-8M	1.5	20	1.50/1.50	0.8	8	12	12	1.2	37C	\$ 540.00
0.75-0.85	PD-800-100-8M	1.00	20	1.20/1.20	0.40	4.0	30	10	1	8J	\$ 265.00
0.75-1.5	PD-0715-8M	1.00	20	1.30/1.30	0.40	4.0	2			8E	\$ 265.00
0.775-0.875	PD-825-100-8M	1.00	20	1.20/1.20	0.40	4.0	30	10	1	8J	\$ 265.00
0.8-0.9	PD-850-100-8M	1.00	20	1.20/1.20	0.40	4.0	30	10	1	8J	\$ 265.00
0.8-1.0	PD-900-200-8M	1.00	18	1.20/1.20	0.40	4.0	30	10	1	8J	\$ 265.00
0.825-0.925	PD-875-100-8M	1.00	20	1.20/1.20	0.40	4.0	30	10	1	8J	\$ 265.00
0.8-2.5	PDR-250-8M	0.80	18	1.50/1.35	0.35	5.0	30	10	1	8K	\$ 250.00
0.8-2.5	PDR-250A-8M	0.80	18	1.50/1.35	0.35	5.0	30	10	1	3	\$ 250.00
0.85-0.95	PD-900-100-8M	1.00	20	1.20/1.20	0.40	4.0	30	10	1	8J	\$ 265.00
0.9-1.1	PD-1000-200-8M	1.00	16	1.20/1.20	0.40	4.0	30	10	1	8J	\$ 265.00
1.0-2.0	PDRM-6801-8M	1.0	20	1.50/1.50	0.8	8	6	6	0.6	37A	\$ 420.00
1.0-1.2	PD-1100-200-8M	1.00	15	1.20/1.20	0.40	4.0	30	10	1	8J	\$ 265.00
1.0-2.0	PD-1020-8M	1.00	20	1.35/1.35	0.40	5.0	2	-	-	8F	\$ 340.00
1.0-2.0	PD-2010-8M	0.80	18	1.40/1.40	0.25	4.0	1	-	-	11B	\$ 497.70
1.50-3.0	PD-1530-8M	1.00	20	1.35/1.35	0.40	6.0	2	-	-	8G	\$ 340.00
2.0-4.0	PDRM-6802-8M	1.0	18	1.50/1.50	0.8	10	6	6	0.6	37B	\$ 400.00
2.0-4.0	PD-2040-8M	1.00	20	1.40/1.40	0.40	6.0	2	-	-	8H	\$ 320.00
2.0-4.0	PD-4020-8M	0.90	17	1.40/1.40	0.25	4.0	1	-	-	11C	\$ 497.70
2.0-8.0	PDRM-6807-8M	2.0	15	1.60/1.60	1.2	16	12	12	1.2	37B	\$ 540.00

† CW at common port * Above split loss
‡ Field Replaceable 27GHz SMA

□/□ input / output connector N, SMA, TNC, BNC

 **RF Depot.com Inc.**

Phone 301-595-5395 Fax 301-595-0050

10101 F Bacon Drive Beltsville, MD. 20705

Toll Free 877-RF Depot

POWER DIVIDERS AND COMBINERS

Freq. Range (GHz)	Model No.	Max. Inser. Loss* (dB)	Min. Isol. (dB)	VSWR Max. In/Out	Max. Balance		Average Power † Load VSWR (Watts)			Fig.	Price 4-9 PCS
					(dB)	(Deg.)	1.20	2.0	∞		
8 WAY											
2.0-18.0	PDRM-6808-8M	3.3	15	1.80/1.80	1.8	24	30	30	3.0	37C	\$ 750.00
4.0-8.0	PDRM-6803-8M	1.5	15	1.60/1.60	0.8	16	6	6	0.6	37B	\$ 400.10
4.0-8.0	PD-4080-8M	1.50	18	1.60/1.60	0.50	6.0	2	-	-	8A	\$ 320.00
4.0-8.0	PD-8040-8M	1.40	16	1.50/1.50	0.30	5.0	1	-	-	11D	\$ 497.70
6-18	PDR-1800600-8M	2.00	18	1.50/1.35	0.35	5.0	10	6	0.2	7	\$ 518.00
7.0-12.4	PD-70124-8M	2.00	16	1.80/1.80	0.50	6.0	2	-	-	8B	\$ 340.00
7.0-18.0	PDRM-6810-8M	2.5	15	1.80/1.80	1.5	24	10	10	1.0	37B	\$ 540.00
8.0-12.4	PDRM-6804-8M	1.7	15	1.70/1.70	0.8	16	6	6	0.6	37B	\$ 400.00
8.0-12.4	PD-12480-8M	1.60	15	1.75/1.75	0.45	5.0	1	-	-	11E	\$ 497.70
12.0-18.0	PD-180120-8M	2.00	13	1.80/1.80	0.60	8.0	1	-	-	11E	\$ 497.70
12.0-18.0	PD-12180-8M	2.50	15	2.10/2.10	0.60	6.0	2	-	-	8C	\$ 360.00
12.4-18	PDRM-6805-8M	1.7	15	2.20/2.20	0.8	24	10	10	0.1	37B	\$ 375.00
16.0-24.0	PDR-24C16C-8M‡	2.00	20	2.0/2.0	0.40	6.0	1	-	-		\$ 489.00

† CW at common port * Above split loss
‡ Field Replaceable 27GHz SMA

□ / □ input / output connector N, SMA, TNC, BNC